

Pulse Pattern Generator BPG 50G-TER



(Illustration similiar)

Key Features

- Pulse Pattern Generator for Bipolar Return-To-Zero Pulses with one Data Output
- Gap-Free Operation at Pulse Repetition Rates between 200 MHz and 25 GHz
- 1 GBit Memory for User Programmable Patterns of Variable Length
- Word Repetition Function
- Amplitude Control of Positive and Negative Pulses and Adjustable DC-Offset of Output Signal
- Operation via Front Panel or USB-Interface
- Optionally Available:
 - Internal Clock Generator
 - Extended Pattern Memory of 2 GBit
 - Other Customer-Specific Features on Demand

The wide-band tuneable pattern generator BPG 50G-TER provides programmable ternary data signals consisting of positive and negative pulses and zeros. An external clock signal between 200 MHz and 25 GHz is needed to provide the time base for operation. The generator is jitter-transparent and follows even abrupt frequency changes.

The length of the user pattern is variable from 16 digits up to 536 870 912 digits and is repeated periodically. Each digit can be set to a positive pulse, a negative pulse or to zero.

The pattern memory can be split in 2, 4 or 8 parts to toggle synchronously between different waveforms. Two short user pattern of 16 digits and 128 digits length are programmable via the front panel.

The pattern generator provides a clock and two data outputs. The output amplitude of the positive and negative pulses of the ternary data signal as well as the DC-offset is independently adjustable.

At the front panel several trigger signals, e.g. a divided clock signal and the word frame trigger signal, are available.

The instrument is remotely controlled via its USB-interface. An easy-to-use graphical user interface is included in the supplied software and allows simple operation by mouse-clicking. Additionally SCPI commands may be used to control the instrument.

Clock Source

The clock source determines the time base for operation. All output signals are derived from it. The pattern generator is operated with a clock signal equal to the output data rate, i.e. with a clock signal of 25 GHz the instrument generates output pulses with a repetition rate of 25 GHz. There are two main clock sources:

Internal

The internal quartz controlled clock generator provides clock signals in the range from 200 MHz to 25 GHz with a resolution of exactly 1 mHz.

External

The clock signal connected to the instruments *Clock Input* is used as system clock. The clock input is jitter-transparent and the instrument follows even abrupt frequency changes of the externally attached signal. The maximum input clock frequency equals 25 GHz. All instrument modes are available in both internal and external clock mode.

10 MHz Reference Input

A 10 MHz reference clock signal can be applied to the reference clock input on the instruments rear panel. This clock signal is used as reference for all timing parameters.

10 MHz Reference Output

The 10 MHz reference clock output signal can be used to synchronize the time base of other instruments to the time base of the pattern generator.

Clock Output

The single-ended clock output provides a clock signal equal to the system clock signal. The AC-coupled CML output signal has an amplitude of $400 \text{ mV}_{pp} \pm 100 \text{ mV}$ into 50Ω .

Pattern

User Programmable Data

Arbitrary user pattern data up to a maximum length of 512 M Digit can be generated. The pattern length can be set in steps of 128 digits. The programmed bit sequence is generated periodically. Additionally the pattern memory can be split in 2, 4 or 8 parts to toggle synchronously between different waveforms. Optionally the pattern generator is available with an extended pattern memory of 1024 M Digit.

RZ

Return to zero pulse format. The output signal returns to zero (low level) after each positive or negative bit and stays at low level for 0 bits.

Output Amplitudes

The amplitude of the positive and negative pulses of the ternary signal can be adjusted independently and for both data outputs separately. This means four amplitude voltages can be independently set and changed:

- $V_{DataA1,+}$ and $V_{DataA1,-}$ define the amplitude of the positive and negative pulses respectively of the **Data A1** output signal
- $V_{DataA2,+}$ and $V_{DataA2,-}$ define the amplitude of the positive and negative pulses respectively of the **Data A2** output signal

The adjustment range for all voltages is 150 mV to 250 mV ($\pm 10\%$ into 50Ω).




Figure 1: Output Pattern with four different Amplitude Settings

Offset

A DC-offset between 0 V and +1 V can be added to the output signal. The DC-offset can be set independently for the *Data A1* and *Data A2* outputs.

Duty Cycle

The duty cycle of the positive and negative RZ pulses can be adjusted independently for each output channel to optimize the output pulse shape.




Figure 2: Output Signals with different Duty Cycle

Word Repetition

For the long user pattern a word repetition function is available that allows to generate patterns with a repetition rate below 1 Hz at the maximum pulse repetition rate of 25 GHz.

The word repetition is selectable between 1 (no repetition) and 32, i. e. each 128 digits long word of the pattern memory is repeated 32-times. Additionally

it is possible to repeat fractional words of 32 and 64 digits length.

Word Fraction	Word Repetition
1 (≥ 128 Digit)	1, 2, 3, ..., 32
2 (≥ 64 Digit)	2, 4, 6, ..., 64
4 (≥ 32 Digit)	2, 4, 8, 12, ..., 128

Table 1: Word Fraction and Word Repetition Factors

During normal operation (Word Repetition = 1 and Word Fraction = 1) the words of the programmed pattern are generated successively in the generator and repeated periodically when the pattern end is reached.



Figure 3: Pattern consisting of 4 words A, B, C and D of each 128 digits length

The *Word Repetition* and *Word Fraction* functions allow to extend the length of the generated pattern by repeatedly generating the words or fractional words of the programmed pattern according to the selected repetition factors. The following figures illustrate this at the example of a 128 digits long word $A = A_1|A_2|A_3|A_4$ in a pattern consisting of the 4 words A, B, C and D.




Figure 4: *Word Fraction* and *Word Repetition* in a pattern consisting of the words A, B, C and D

Bit Shift

The bit shift functionality allows to delay the output signal by n bits ($0 \leq n \leq 2^{36}$) to compensate for cable delays.




Figure 5: Example of a pulse pattern delayed by 2 bits

Jitter Insertion

When the external clock input is used the pattern generator follows exactly the externally connected frequency. By modulating the external clock source jitter-modulated data signals can be generated.

Trigger Signals

Trigger Output

The trigger output provides a divided clock signal (Bit Rate)/8 or a pattern synchronous trigger signal (word-frame trigger signal).

Graphical User Interface

The graphical user interface allows to change all device settings and program the user pattern by simple mouse-clicking. The last settings are automatically saved when power is turned off.




Figure 6: Graphical User Interface of the Operating Software

SCPI Remote Control

The pattern generator can be remotely controlled via SCPI commands, a standardized instruction set for controlling and programming measurement instruments. The SCPI commands are transferred to the instrument in ASCII text format and may be generated using any programming language and development environment.

Options

Internal Clock Generator

The internal synthesizer generates clock signals between 200 MHz and 25 GHz with a resolution of exactly 1 mHz. An internal relay allows to switch between internal and external clock source. The 10 MHz reference input and output make it possible to synchronize the pulse pattern generator to external timing references or other instruments in the measurement set up.

Extended Pattern Memory

The extended pattern memory of 2 GBit allows to generate user patterns of 1 073 741 824 digits length.

Technical Specifications

Bipolar Pattern Generator BPG 50G-TER

External Clock

Frequency Range	200 MHz ... 25 GHz, gap-free
Each clock cycle represents one positive or negative RZ pulse, the pulse width equals half the clock period.	
Clock Input	200 MHz ... 25 GHz
Impedance	$R_i = 50 \Omega$, $ r < 0,2$
Input Amplitude	$U_i = 0.5 \dots 1 V_{pp}$
Connector	50 Ω SMA
Frequency Counter	6-digit frequency display

Pattern Generation

Data Format	Bipolar Return-to-zero pulses
Pulse Repetition Rate	According to Input Clock, 200 MHz ... 25 GHz
Programmable Patterns	<ol style="list-style-type: none"> 1. 16-digit pulse pattern (programmable via front panel) 2. 128-digit pulse pattern (programmable via front panel) 3. Pulse pattern of length $128 * m$ digit ($m = 1, 2, \dots, 2^{22}$) (=max. 268.435.456 ternary coded digits) 4. Pulse pattern consisting of two parts, each of length $128 * m$ digit ($m = 1, 2, \dots, 2^{21}$), synchronously selectable 5. Pulse pattern consisting of four parts, each of length $128 * m$ digit ($m = 1, 2, \dots, 2^{20}$), synchronously selectable 6. Pulse pattern consisting of eight parts, each of length $128 * m$ digit ($m = 1, 2, \dots, 2^{19}$), synchronously selectable <p>All patterns are programmable and selectable via the USB-interface. The programmed patterns should have approximately the same number of positive and negative pulses</p>
Word Repetition	Repetition function for the $128/n$ digits ($n \in \{1, 2, 4\}$) long fractional words of the programmed pattern, repetition factors: $1*n$, $2*n$, $3*n$, ..., $32*n$

Pattern Memory	1 073 741 824 bits (= 536 870 912 digits)
----------------	---

Programmable Pattern Length	$128 * m$ digits, ($m = 1, 2, \dots, 2^{22}$)
-----------------------------	---

Data Outputs

Single-ended data outputs A1 and A2 for ternary data code $-V/0/+V$, DC-coupled	
Connector	2.92 mm, 50 Ω
Amplitude	Amplitude voltages $V_{DataA1,+}$, $V_{DataA1,-}$, $V_{DataA2,+}$ and $V_{DataA2,-}$ independently adjustable in the range of 150 mV to 250 mV ($\pm 10\%$ into 50 Ω)
Rise-/Falltime	< 12 ps (20/80%)
Jitter (pp)	< 10 ps
Polarity	Reversible, positive and negative pulses interchanged
Offset	DC-Offset regulation for the data output for zero-potential adjustment

PG 50G-TER

Trigger Outputs

Clock Output	1. Clock, Amplitude: $0.4 V_{pp} \pm 0.1 V$ AC-coupled, 50Ω SMA
Trigger Outputs	1. CML: $0 V / -0.4 V$ into 50Ω SMA Clock/8 or Word Frame Trigger selectable, Pulse width: 64 clock periods 2. TTL Word Frame Trigger 1: $0 V / 3 V$ SMA (on rear panel), Trigger frequency according to the chosen pattern, pulse width selectable: 1024, 2048, 3072 or 4096 clock periods 3. TTL Word Frame Trigger 2: $0 V / 3 V$ SMA (on rear panel), Trigger frequency according to the chosen pattern, pulse width selectable: 1024, 2048, 3072 or 4096 clock periods

General Information

Interface	USB-port, max. data transmission rate 8 MByte/s
Software	Graphical User Interface for operation and pattern programming
Dimensions	19" Desktop W x H x D = 462 x 135 x 435 mm
Weight	approx. 12 kg
Power Supply	100 V-240 V/50 Hz-60 Hz/100 VA

Optionally Available

Option 1: Internal Clock Generator

Internal or External Clock Selectable
Frequency Range 200 MHz to 25 GHz
Resolution 1 mHz
Reference 10 MHz Reference Clock Input and Output

Option 2: Extended Pattern Memory

Pattern Memory 2 GBit (=1 073 741 824 digits)


Option 3: Extended Output Amplitude

Single-ended data outputs A1 and A2 for ternary data code $-V / 0 / +V$, DC-coupled
Connector 2.92 mm, 50Ω
Amplitude Amplitude voltages $V_{DataA1,+}$, $V_{DataA1,-}$, $V_{DataA2,+}$ and $V_{DataA2,-}$ independently adjustable in the range of 150 mV to 350 mV ($\pm 10\%$ into 50Ω)
Rise-/Falltime < 10 ps (20/80%)
Jitter (pp) < 10 ps
Polarity Reversible, positive and negative pulses interchanged
Offset DC-Offset regulation for the data output for zero-potential adjustment

Output Signals

All oscilloscopes in this section were taken using the Agilent N1000A sampling oscilloscope and the sampling module N1045A (60 GHz cut-off frequency).

Typical Output Waveforms



Output at 25 GHz Clock Rate

Ordering Information

SYMPULS GmbH

Römerstr. 39
D-52064 Aachen

Phone: +49 241 35334
Fax: +49 241 35335
Email: mail@sympuls-aachen.de
Internet: www.sympuls-aachen.de

Included in delivery:

- BPG 50G-TER
- 115/230 V Mains, User Manual, USB Cable Set
- CD-ROM with Device Driver and Operating Software

**The instrument is produced by SYMPULS in Germany.
We offer a reliable service and 24 month warranty.**